

## M831



- DC Voltage: 200m/2/20/200V ± 0.5%  
1000V ± 0.8%
- AC Voltage: 200/750V ± 1.2%
- DC Current: 200 μ / 2m/20mA ± 1.0%  
200mA ± 1.5% 10A ± 3.0%
- Resistance:  
200/2k/20k/200k Ω ± 0.8%, 2M Ω ± 1.0%
- Continuity checking with buzzer
- Diode check:  
Test current 0.8mA, Test voltage 3V
- Power source: 6F22(9V) x 1
- Size Weight: 70 x 126 x 24mm
- 170g(including battery)
- Display: 15 x 46mm LCD

## M830B



- DC Voltage: 200m/2/20/200V ± 0.5%  
1000V ± 0.8%
- AC Voltage: 200/750V ± 1.2%
- DC Current: 200 μ / 2m/20mA ± 1.0%  
200mA ± 1.5% 10A ± 3.0%
- Resistance:  
200/2k/20k/200k Ω ± 0.8%, 2M Ω ± 1.0%
- Diode check:  
Test current 0.8mA, Test voltage 3V
- hFE: 1~1000
- Power source: 6F22(9V) x 1
- Size Weight: 70 x 126 x 24mm
- 170g(including battery)
- Display: 15 x 46mm LCD

**MODEL M 830 Bz  
IS SAME AS MODEL  
M 832  
BUT W/O THE SQUARE WAVE O/P**

## M832



- DC Voltage: 200m/2/20/200V ± 0.5%  
1000V ± 0.8%
- AC Voltage: 200/750V ± 1.2%
- DC Current: 2m/20mA ± 1.0%  
200mA ± 1.5% 10A ± 3.0%
- Resistance:  
200/2k/20k/200k Ω ± 0.8%, 2M Ω ± 1.0%
- Continuity checking with buzzer
- Diode check:  
Test current 0.8mA, Test voltage 3V
- hFE: 1~1000
- Signal Generator: 50Hz square wave
- Power source: 6F22(9V) x 1
- Size Weight: 70 x 126 x 24mm
- 170g(including battery)
- Display: 15 x 46mm LCD

## M838



- DC Voltage: 200m/2/20/200V ± 0.5%  
1000V ± 0.8%
- AC Voltage: 200/750V ± 1.2%
- DC Current: 2m/20mA ± 1.0%  
200mA ± 1.5% 10A ± 3.0%
- Resistance:  
200/2k/20k/200k Ω ± 0.8%, 2M Ω ± 1.0%
- Continuity checking with buzzer
- Diode check:  
Test current 0.8mA, Test voltage 3V
- Temperature: -20°C ~ 1000°C
- hFE: 1~1000
- Power source: 6F22(9V) x 1
- Size Weight: 70 x 126 x 24mm
- 170g(including battery)
- Display: 15 x 46mm LCD

